

# DMX CHANNELS / VALUES / FUNCTIONS

DMX CHANNELS / VALUES / FUNCTIONS (3 Modes 6 Channels)				
SUPPORTS SOFTWARE VERSION 1.0				
MODE (1,2 and 6) / CHANNEL			VALUE	FUNCTION
1ch	2ch	6ch		
1	1	1	0 - 31 32 - 255	<b>Smoke ON/OFF</b> Off ON
	2	2	0 - 28 29 - 255	<b>Volume</b> 10% 11-100%
		3	0 - 10 11 - 249 250 - 255	<b>Duration</b> 10 Seconds 11-249 Seconds 250 Seconds
		4	0 - 4 5 - 10 11 - 249 250 - 255	<b>Interval</b> 0 Seconds 10 Seconds 11-249 Seconds 250 Seconds
		5	0 - 63 64 - 127 128 - 191 192 - 255	<b>Preset Temperature</b> 65°C 70°C 75°C 80°C
		6	0 - 31 32 - 255	<b>Heater</b> Off On