

6 CH	10 CH	11 CH	16 CH	48 CH	57 CH	96 CH	VALUES	FUNCTIONS
1	1	1	1				000-255	RED (ALL LEDS) 0-100%
2	2	2	2				000-255	GREEN (ALL LEDS) 0-100%
3	3	3	3				000-255	BLUE (ALL LEDS) 0-100%
4	4	4	4				000-255	WHITE (ALL LEDS) 0-100%
5	5	5	5				000-255	AMBER (ALL LEDS) 0-100%
6	6	6	6				000-255	UV (ALL LEDS) 0-100%
				1	1	1	000-255	RED (ZONE #1) 0-100%
						2		RED FINE (ZONE #1)
				2	2	3	000-255	GREEN (ZONE #1) 0-100%
						4		GREEN FINE (ZONE #1)
				3	3	5	000-255	BLUE (ZONE #1) 0-100%
						6		BLUE FINE (ZONE #1)
				4	4	7	000-255	WHITE (ZONE #1) 0-100%
						8		WHITE FINE (ZONE #1)
				5	5	9	000-255	AMBER (ZONE #1) 0-100%
						10		AMBER FINE (ZONE #1)
				6	6	11	000-255	UV (ZONE #1) 0-100%
						12		UV FINE (ZONE #1)
				7	7	13	000-255	RED (ZONE #2) 0-100%
						14		RED FINE (ZONE #2)
				8	8	15	000-255	GREEN (ZONE #2) 0-100%
						16		GREEN FINE (ZONE #2)
				9	9	17	000-255	BLUE (ZONE #2) 0-100%
						18		BLUE FINE (ZONE #2)
				10	10	19	000-255	WHITE (ZONE #2) 0-100%
						20		WHITE FINE (ZONE #2)

6 CH	10 CH	11 CH	16 CH	48 CH	57 CH	96 CH	VALUES	FUNCTIONS
				11	11	21	000-255	AMBER (ZONE #2) 0-100%
						22		AMBER FINE (ZONE #2)
				12	12	23	000-255	UV (ZONE #2) 0-100%
						24		UV FINE (ZONE #2)
				13	13	25	000-255	RED (ZONE #3) 0-100%
						26		RED FINE (ZONE #3)
				14	14	27	000-255	GREEN (ZONE #3) 0-100%
						28		GREEN FINE (ZONE #3)
				15	15	29	000-255	BLUE (ZONE #3) 0-100%
						30		BLUE FINE (ZONE #3)
				16	16	31	000-255	WHITE (ZONE #3) 0-100%
						32		WHITE FINE (ZONE #3)
				17	17	33	000-255	AMBER (ZONE #3) 0-100%
						34		AMBER FINE (ZONE #3)
				18	18	35	000-255	UV (ZONE #3) 0-100%
						36		UV FINE (ZONE #3)
				19	19	37	000-255	RED (ZONE #4) 0-100%
						38		RED FINE (ZONE #4)
				20	20	39	000-255	GREEN (ZONE #4) 0-100%
						40		GREEN FINE (ZONE #4)
				21	21	41	000-255	BLUE (ZONE #4) 0-100%
						42		BLUE FINE (ZONE #4)
				22	22	43	000-255	WHITE (ZONE #4) 0-100%
						44		WHITE FINE (ZONE #4)
				23	23	45	000-255	AMBER (ZONE #4) 0-100%
						46		AMBER FINE (ZONE #4)
				24	24	47	000-255	UV (ZONE #4) 0-100%
						48		UV FINE (ZONE #4)

6 CH	10 CH	11 CH	16 CH	48 CH	57 CH	96 CH	VALUES	FUNCTIONS
				25	25	49	000-255	RED (ZONE #5) 0-100%
						50		RED FINE (ZONE #5)
				26	26	51	000-255	GREEN (ZONE #5) 0-100%
						52		GREEN FINE (ZONE #5)
				27	27	53	000-255	BLUE (ZONE #5) 0-100%
						54		BLUE FINE (ZONE #5)
				28	28	55	000-255	WHITE (ZONE #5) 0-100%
						56		WHITE FINE (ZONE #5)
				29	29	57	000-255	AMBER (ZONE #5) 0-100%
						58		AMBER FINE (ZONE #5)
				30	30	59	000-255	UV (ZONE #5) 0-100%
						60		UV FINE (ZONE #5)
				31	31	61	000-255	RED (ZONE #6) 0-100%
						62		RED FINE (ZONE #6)
				32	32	63	000-255	GREEN (ZONE #6) 0-100%
						64		GREEN FINE (ZONE #6)
				33	33	65	000-255	BLUE (ZONE #6) 0-100%
						66		BLUE FINE (ZONE #6)
				34	34	67	000-255	WHITE (ZONE #6) 0-100%
						68		WHITE FINE (ZONE #6)
				35	35	69	000-255	AMBER (ZONE #6) 0-100%
						70		AMBER FINE (ZONE #6)
				36	36	71	000-255	UV (ZONE #6) 0-100%
						72		UV FINE (ZONE #6)
				37	37	73	000-255	RED (ZONE #7) 0-100%
						74		RED FINE (ZONE #7)
				38	38	75	000-255	GREEN (ZONE #7) 0-100%
						76		GREEN FINE (ZONE #7)

6 CH	10 CH	11 CH	16 CH	48 CH	57 CH	96 CH	VALUES	FUNCTIONS
				39	39	77	000-255	BLUE (ZONE #7) 0-100%
						78		BLUE FINE (ZONE #7)
				40	40	79	000-255	WHITE (ZONE #7) 0-100%
						80		WHITE FINE (ZONE #7)
				41	41	81	000-255	AMBER (ZONE #7) 0-100%
						82		AMBER FINE (ZONE #7)
				42	42	83	000-255	UV (ZONE #7) 0-100%
						84		UV FINE (ZONE #7)
				43	43	85	000-255	RED (ZONE #8) 0-100%
						86		RED FINE (ZONE #8)
				44	44	87	000-255	GREEN (ZONE #8) 0-100%
						88		GREEN FINE (ZONE #8)
				45	45	89	000-255	BLUE (ZONE #8) 0-100%
						90		BLUE FINE (ZONE #8)
				46	46	91	000-255	WHITE (ZONE #8) 0-100%
						92		WHITE FINE (ZONE #8)
				47	47	93	000-255	AMBER (ZONE #8) 0-100%
						94		AMBER FINE (ZONE #8)
				48	48	95	000-255	AMBER (ZONE #8) 0-100%
						96		UV FINE (ZONE #8)
		7	7		49		000-031 032-063 064-095 096-127 128-159 160-191 192-223 224-255	STROBE LED OFF LED ON STROBING SLOW - FAST LED ON PULSE STROBING SLOW - FAST LED ON RANDOM STROBING SLOW - FAST LED ON
	7	8	8		50		000-255	MASTER DIMMER 8BIT 0-100%
	8	9	9		51		000-255	MASTER DIMMER FINE 16BIT 0-100%

6 CH	10 CH	11 CH	16 CH	48 CH	57 CH	96 CH	VALUES	FUNCTIONS
			10				000-255	COLOR MACROS SEE PAGES 17-18 FOR COLOR MACRO CHART
			11		52		000-010 011-026 027-043 044-060 061-076 077-093 094-110 111-126 127-143 144-160 161-176 177-193 194-210 211-226 227-255	AUTO PROGRAMS NO FUNCTION DREAM METEOR FADE CHANGE FLOW 1 FLOW 2 FLOW 3 FLOW 4 FLOW 5 FLOW 6 FLOW 7 FLOW 8 FLOW 9 NO FUNCTION
			12		53		000-255	AUTO PROGRAM SPEED SLOW - FAST
			13		54		000-255	AUTO PROGRAM FADE* SLOW - FAST
			14		55		000-020 021-040 041-060 061-080 081-100 101-255	DIMMER MODE STANDARD STAGE TV ARCHITECTURAL THEATRE DEFAULT TO UNIT SETTING
	9	10	15		56		000-015 016-030 031-045 046-060 061-075 076-090 091-105 106-120 121-135 136-150 151-165 166-180 181-195 196-210 211-225 226-255	LED REFRESH RATE DEFAULT TO UNIT SETTING 900HZ 1000HZ 1100HZ 1200HZ 1300HZ 1400HZ 1500HZ 2500HZ 4000HZ 5000HZ 10000HZ 15000HZ 20000HZ 25000HZ OFF
	10	11	16		57		000-020 021-040 041-060 061-080 081-100 101-120 121-255	GAMMA DEFAULT TO UNIT SETTING 2.0 2.2 2.4 2.6 2.8 OFF